
Application Note

TRANSITIONING FROM THE CS8405A TO THE CS8406

by Sean Davis

1. Introduction

The CS8406 was designed as a pin and function compatible update for the CS8405A to add 192 kHz sample rate capability and offer over 1/3 less total power consumption than the CS8405A. This document outlines the considerations that need to be accounted for when making the transition. Please refer to the latest revision of each part's datasheet for a detailed description of part operation.

2. Power Supply

The VD+ supply of the CS8405A operates only at 5.0 V \pm 10%, while the VD supply of the CS8406 operates at either 3.3 V or 5.0 V \pm 5%. However, when the CS8406 is operated with VD = 5.0 V, certain conditions apply:

- V_{IH} (Min) for the CS8406 = 2.75 V. V_{IH} (Min) for the CS8405A = 2.0 V.
- In power down mode, it is recommended that all inputs be driven low to minimize current consumption.

3. Software Mode

Shown in Table 2 on page 2 is a list of pin numbers and their corresponding pin names for both parts when operated in Software mode. The register settings for the CS8405A are compatible with the CS8406.

4. Hardware Mode

Shown in Table 3 on page 3 is a list of pin numbers and their corresponding pin names for both parts when operated in Hardware mode.

5. CS8406 Test Pins

The CS8406 has several pins labeled as TEST. These pins are unused inputs in either Software or Hardware mode. It is recommended that these pins be tied to a supply (VL or GND) to minimize leakage current.

When transitioning from the CS8405A to the CS8406, some of the TEST pins on the CS8406 may be left floating due to corresponding pins on the CS8405A being labeled as no connects. The CS8406 will operate the same if these pins are left floating, however current consumption from VL will increase by 25 μ A per pin that is left floating. As the CS8406 consumes much less current than the CS8405A, this should not be a concern to the user.

6. Output Resistance

The typical output resistance of the transmitter pins changed from the CS8405A to the CS8406. The value of the external series resistor placed on the transmitter pins should be modified appropriately to account for this change. See the latest CS8406 datasheet for details on selecting the value of the external resistor.

Parameter	VL = 3.3 V	VL = 5 V	Unit
TXP/TXN CS8405A Output Resistance	40	26	Ω
TXP/TXN CS8406 Output Resistance	33.5	26.5	Ω

Table 1. Transmitter Output Resistance

Pin Number	CS8405A Pin Name	CS8406 Pin Name	Differences
1	SDA / CDOUT	SDA / CDOUT	CS8405A I ² C™ is only supported at VL+ = 5.0 V. CS8406 allows I ² C operation at VL = 3.3 V or 5.0 V.
5	DGND2	TEST	See “CS8406 Test Pins” on page 1.
6	VD+	VD	See “Power Supply” on page 1.
7	DGND4	TEST	See “CS8406 Test Pins” on page 1.
8	DGND3	TEST	See “CS8406 Test Pins” on page 1.
10	NC1	TEST	See “CS8406 Test Pins” on page 1.
11	NC2	TEST	See “CS8406 Test Pins” on page 1.
16	NC3	TEST	See “CS8406 Test Pins” on page 1.
17	NC4	TEST	See “CS8406 Test Pins” on page 1.
18	NC5	TEST	See “CS8406 Test Pins” on page 1.
21	OMCK	OMCK	CS8405A OMCK clock ratios can be 256*Fs, 384*Fs, or 512*Fs. CS8406 OMCK clock ratios can be 128*Fs, 256*Fs, 384*Fs, or 512*Fs.
23	VL+	VL	For both parts, the VL supply can operate at 3.3 V or 5.0 V.
28	SCL / CCLK	SCL / CCLK	CS8405A I ² C is only supported at VL+ = 5.0 V. CS8406 allows I ² C operation at VL = 3.3 V or 5.0 V.
Pins 2, 3, 4, 9, 12, 13, 14, 15, 19, 20, 22, 24, 25, 26, and 27 have the same functions on both parts.			

Table 2. Software Mode Comparison

Pin Number	CS8405A Pin Name	CS8406 Pin Name	Differences
2	VL2+	TEST	See “CS8406 Test Pins” on page 1.
6	VD+	VD	See “Power Supply” on page 1.
7	DGND4	TEST	See “CS8406 Test Pins” on page 1.
8	DGND3	TEST	See “CS8406 Test Pins” on page 1.
20	VL3+	HWCK0	Pins 20 and 27 set the OMCK clock ratio for the CS8406. Setting both pins to VL (the recommended setting from the CS8405A datasheet) or both pins to GND will cause the clock ratio to be 256*Fs, the only mode available for the CS8405A.
21	OMCK	OMCK	CS8405A OMCK clock ratio is 256*Fs. CS8406 OMCK clock ratios can be 128*Fs, 256*Fs, or 512*Fs, set by HWCK[0:1].
23	VL+	VL	For both parts, the VL supply can operate at 3.3 V or 5.0 V.
27	VL4+	HWCK1	Pins 20 and 27 set the OMCK clock ratio for the CS8406. Setting both pins to VL (the recommended setting from the CS8405A datasheet) or both pins to GND will cause the clock ratio to be 256*Fs, the only mode available for the CS8405A.
Pins 1, 3, 4, 5, 9, 10, 11, 12, 13, 14, 15, 16, 17, 18, 19, 22, 24, 25, 26, and 28 have the same functions on both parts.			

Table 3. Hardware Mode Comparison

7. Revision History

Revision	Changes
REV1	Initial Release
REV2	Added "Output Resistance" on page 2

Contacting Cirrus Logic Support

For all product questions and inquiries contact a Cirrus Logic Sales Representative.

To find one nearest you go to www.cirrus.com

IMPORTANT NOTICE

Cirrus Logic, Inc. and its subsidiaries ("Cirrus") believe that the information contained in this document is accurate and reliable. However, the information is subject to change without notice and is provided "AS IS" without warranty of any kind (express or implied). Customers are advised to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgment, including those pertaining to warranty, indemnification, and limitation of liability. No responsibility is assumed by Cirrus for the use of this information, including use of this information as the basis for manufacture or sale of any items, or for infringement of patents or other rights of third parties. This document is the property of Cirrus and by furnishing this information, Cirrus grants no license, express or implied under any patents, mask work rights, copyrights, trademarks, trade secrets or other intellectual property rights. Cirrus owns the copyrights associated with the information contained herein and gives consent for copies to be made of the information only for use within your organization with respect to Cirrus integrated circuits or other products of Cirrus. This consent does not extend to other copying such as copying for general distribution, advertising or promotional purposes, or for creating any work for resale.

CERTAIN APPLICATIONS USING SEMICONDUCTOR PRODUCTS MAY INVOLVE POTENTIAL RISKS OF DEATH, PERSONAL INJURY, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE ("CRITICAL APPLICATIONS"). CIRRUS PRODUCTS ARE NOT DESIGNED, AUTHORIZED OR WARRANTED FOR USE IN PRODUCTS SURGICALLY IMPLANTED INTO THE BODY, AUTOMOTIVE SAFETY OR SECURITY DEVICES, LIFE SUPPORT PRODUCTS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF CIRRUS PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE FULLY AT THE CUSTOMER'S RISK AND CIRRUS DISCLAIMS AND MAKES NO WARRANTY, EXPRESS, STATUTORY OR IMPLIED, INCLUDING THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR PARTICULAR PURPOSE, WITH REGARD TO ANY CIRRUS PRODUCT THAT IS USED IN SUCH A MANNER. IF THE CUSTOMER OR CUSTOMER'S CUSTOMER USES OR PERMITS THE USE OF CIRRUS PRODUCTS IN CRITICAL APPLICATIONS, CUSTOMER AGREES, BY SUCH USE, TO FULLY INDEMNIFY CIRRUS, ITS OFFICERS, DIRECTORS, EMPLOYEES, DISTRIBUTORS AND OTHER AGENTS FROM ANY AND ALL LIABILITY, INCLUDING ATTORNEYS' FEES AND COSTS, THAT MAY RESULT FROM OR ARISE IN CONNECTION WITH THESE USES.

Cirrus Logic, Cirrus, and the Cirrus Logic logo designs are trademarks of Cirrus Logic, Inc. All other brand and product names in this document may be trademarks or service marks of their respective owners.

°C is a trademark of Philips Semiconductor.